

指針絕緣阻抗計

ANALOG INSULATION TESTERS

- 吊線式高品質防震表頭
- 絕緣阻抗三檔量測電壓：250V、500V、1000V
- 兩檔導通測試：0-3Ω(低Ω量測)/0-500Ω
- 絕緣阻抗量測推動電流不小於1mA
- 外來電壓紅色燈(LED)警示
- 關機後自動放電
- 檢查電源大小功能
- 電池能量消耗量低
- 刻度板有反射鏡
- 使用測試旋鈕可作長時間量測
- 保險絲保護設計
- 符合IEC 61010-1 CAT III 600V
- 符合英國第16版本(BS16th)



CE

2132 IN

電氣規格(23±5°C ≤ 80%RH)

絕緣阻抗(MΩ)

量測檔位	250V	500V	1000V
量測電壓最大容許	額定電壓+10%		
量測範圍	0-100MΩ	0-200MΩ	0-400MΩ
中央刻度	1MΩ	2MΩ	4MΩ
刻度板識讀	x 1/2	x 1	x 2
量測推動電流	1.3mA 直流電流		
準確度	±3%刻度指示值		

導通測試(Ω)

量測檔位	0-3Ω/0-500Ω
短路電流輸出	≥ 205mA
準確度	±1.5%刻度長

交流電壓(ACV)

量測範圍	0-600V 交流電壓
準確度	±3%刻度長

一般敘述

外來電壓警示	外來電壓交流電壓 70V / 直流電壓 90V 時，紅燈(LED)亮，蜂鳴器響應在 24V 交直流電壓輸入時。
檢查電池能量	8V-13V 時指針會指示在 OK 範圍內，在量測時電池 OK(在 8V 以上)燈會亮
使用電池	1.5V(AA) x 8(顆)
外形尺寸	210(長) x 210(寬) x 100(高)公厘
重量	約 1400 克(含電池)
附件	測試線 x 1(組) · 說明書 x 1(本) · 肩帶 x 1(條) · 電池保險絲(0.5A,250V) x 1(支)

FEATURES

- High quality Taut Band movement.
- Three insulation test voltages (DC) : 250V, 500V, 1000V.
- Two continuity test on low ohms : 500Ω & 3Ω
- Small and light weight.
- AC voltmeter with linear scale up to 600 Vac.
- 205mA continuity short circuit current.
- 1mA test current on insulation test at nominal voltage.
- Automatic discharge of capacitance and inductive circuit with charge stored in the circuit under test.
- Live warning and display of external voltage presence.
- Fuse, air gap, crowbar and overload protected.
- On line battery monitoring shows if battery is ok.
- Very low battery consumption.
- On-Load battery check (240mA load for worst case).
- Mirror scale.
- Push and turn locking switch for long and hand free testing.
- EN 61010-1 CAT III 600V
EN 61326-1
- BS 16th edition.

SPECIFICATIONS

Insulation Resistance

Test Voltage (DC V)	250V	500V	1000V
Output Ranges on open circuit	Rated test Voltage±10%		
Measuring Ranges	0-100MΩ	0-200MΩ	0-400MΩ
Mid-Scale Value	1MΩ	2MΩ	4MΩ
Scale Multiplier	x1/2	x1	x2
Accuracy	±3% of indicated value		
Output Short-Circuit Current	1.3mA		

Continuity

Measuring Ranges	3Ω/500Ω
Output Short-Circuit Current	205mA
Accuracy	±1.5% of scale length



TEL-AL11-5

BET-1800



CE

2132 IN

AC Voltage

AC Voltage Range	0-600VAC
Accuracy	±3% of scale length

General

Voltage Warning	Warning light circuit live lit from 90Vdc/70Vac Buzzer beep from 24Vac/dc
Battery Check	Battery check indicate good batteries from 8Vdc to 13Vdc during a load test of 240mA
Battery OK	Battery OK LED from 8Vdc and is operative while testing
Power source	1.5V(SUM-3) x 8. Type AA.
Dimension	210(L) x 210(W) x 100(D)mm
Weight	Approx. 1400g(battery included)
Accessories	Test leads Fuse(0.5A 250V) Shoulder belt Instruction manual Batteries



STANDARD ELECTRIC WORKS CO., LTD.
5F.,NO.105, Jhongcheng Rd., Tucheng Dist.,
New Taipei City 23674, Taiwan (R.O.C.)
TEL: 886-2-22681528 FAX: 886-2-22681529
<http://www.sew.com.tw> e-mail: sales@sew.com.tw